



**Tripp Lite**  
 1111 West 35th Street  
 Chicago, IL 60609 USA  
 Telephone: +(773) 869 1234  
 E-mail: [saleshelp@tripplite.com](mailto:saleshelp@tripplite.com)

## Model #: LR1000

**Line Conditioner / AVR System - Automatic voltage regulator / power conditioner / AC surge suppressor**



### Highlights

- Automatically adjusts low or high voltage without the aid of a battery
- 1000 watts continuous
- 2 NEMA 5-15R and 2 C13 outlets
- Includes a uniplug adapter

### Description

Tripp Lite's LR1000 automatic voltage regulation system offers complete protection from brownouts, overvoltages and transient surges for computers, printers, fax machines and more. Transformer-based voltage correction circuits maintain usable 220-240V nominal AC output during brownouts as low as 168V and overvoltages to 278V. Network grade equipment protection offers AC surge and noise suppression. Supports heavy loads up to 1000 watts. Includes 4 protected outlets (2 x 5-15R; 2 x C13), 2m-line cord and 7 diagnostic LEDs that display incoming voltage level, surge protection status and line fault conditions. 2-year warranty.

#### Applications

- Maintains usable output voltage during severe brownouts and overvoltages for printers, fax machines, computers, audio/video equipment, CAD/CAM/CAE workstations, network nodes, file servers, phone systems, point-of-sale terminals, and other applications requiring steady input power.

#### Package Includes

- LR1000 Line Conditioner
- UNIPLUG Plug Adapter
- International Ground Pin Adapter
- Optional 2m C13-to-NEMA 5-15P input cord
- Instruction manual and warranty information

### Features

- Maintains usable 220-240V nominal output during brownouts as low as 168V and overvoltages as high as 278V
- 1000 watts output power rating supports heavy 220-240V loads up to 4 amps
- Network grade surge suppression
- EMI/RFI noise filtering
- 7 diagnostic LEDs indicate input voltage levels, surge suppression status and line fault conditions
- 2 protected NEMA5-15R and 2 C13 outlets
- 2m detachable AC power cord with standard NEMA5-15P input plug
- 2 year manufacturers product warranty

### Specifications

OUTPUT	
Output watts	1000

<b>Output nominal voltage</b>	230V, 50 / 60Hz
<b>Outlet quantity / type</b>	2 C13 and 2 NEMA 5-15R (includes 1 uniplug adapter that converts one of the built-in outlets to accept a variety of country specific plug types)
<b>INPUT</b>	
<b>Input cord length (ft.)</b>	6
<b>Input cord length (m)</b>	1.83
<b>LEDS ALARMS &amp; SWITCHES</b>	
<b>Front panel LEDs</b>	7 LEDs show incoming voltage status, protection present and line fault conditions
<b>PHYSICAL</b>	
<b>Shipping weight (lbs)</b>	9.00
<b>Shipping weight (kg)</b>	4.08
<b>Unit Dimensions (HWD/in)</b>	6.75 x 5.75 x 6.75
<b>Material of construction</b>	Plastic
<b>Form factors supported</b>	Box-shaped power tap format
<b>WARRANTY</b>	
<b>Product Warranty Period (U.S., Canada &amp; Puerto Rico)</b>	2-year limited warranty

## Related Items

### Optional Products

Product Type	Related Model	Description	Qty.
Plug Adapters	<a href="#">UNIPLUGINT</a>	Power Management Tools - Outlet Adapter	1

More information, including related products, owner's manuals, and additional technical specifications, can be found online at [www.tripplite.com/en/products/model.cfm?txtModelID=2818](http://www.tripplite.com/en/products/model.cfm?txtModelID=2818).

Copyright © 2011 Tripp Lite. All rights reserved. All trademarks are the sole property of their respective owners. Tripp Lite has a policy of continuous improvement. Specifications are subject to change without notice. Photos may differ slightly from final products.